

1. Description


1.1. Project

| | |
|-----------------|--------------------|
| Project Name | sd_LEDSigne_v100 |
| Board Name | sd_LEDSigne_v100 |
| Generated with: | STM32CubeMX 4.16.0 |
| Date | 08/23/2016 |

1.2. MCU

| | |
|----------------|---------------|
| MCU Series | STM32F4 |
| MCU Line | STM32F411 |
| MCU name | STM32F411RETx |
| MCU Package | LQFP64 |
| MCU Pin number | 64 |


2. Pinout Configuration



3. Pins Configuration

| Pin Number LQFP64 | Pin Name (function after reset) | Pin Type | Alternate Function(s) | Label |
|----------------------|---------------------------------------|----------|--------------------------|-------|
| 1 | VBAT | Power | | |
| 3 | PC14-OSC32_IN | I/O | RCC_OSC32_IN | |
| 4 | PC15-OSC32_OUT | I/O | RCC_OSC32_OUT | |
| 5 | PH0 - OSC_IN | I/O | RCC_OSC_IN | |
| 6 | PH1 - OSC_OUT | I/O | RCC_OSC_OUT | |
| 7 | NRST | Reset | | |
| 12 | VSSA | Power | | |
| 13 | VDDA | Power | | |
| 16 | PA2 | I/O | USART2_TX | |
| 17 | PA3 | I/O | USART2_RX | |
| 18 | VSS | Power | | |
| 19 | VDD | Power | | |
| 21 | PA5 | I/O | SPI1_SCK | |
| 22 | PA6 | I/O | SDIO_CMD | |
| 23 | PA7 | I/O | SPI1_MOSI | |
| 29 | PB10 | I/O | I2C2_SCL | |
| 30 | VCAP1 | Power | | |
| 31 | VSS | Power | | |
| 32 | VDD | Power | | |
| 36 | PB15 | I/O | SDIO_CK | |
| 39 | PC8 | I/O | SDIO_D0 | |
| 40 | PC9 | I/O | SDIO_D1 | |
| 42 | PA9 | I/O | SDIO_D2 | |
| 47 | VSS | Power | | |
| 48 | VDD | Power | | |
| 52 | PC11 | I/O | SDIO_D3 | |
| 55 | PB3 | I/O | I2C2_SDA | |
| 56 | PB4 | I/O | SPI1_MISO | |
| 58 | PB6 | I/O | I2C1_SCL | |
| 59 | PB7 | I/O | I2C1_SDA | |
| 60 | BOOT0 | Boot | | |
| 63 | VSS | Power | | |
| 64 | VDD | Power | | |

4. Clock Tree Configuration



5. IPs and Middleware Configuration

5.1. I2C1

I2C: I2C

5.1.1. Parameter Settings:

Master Features:

| | |
|----------------------|---------------|
| I2C Speed Mode | Standard Mode |
| I2C Clock Speed (Hz) | 100000 |

Slave Features:

| | |
|----------------------------------|----------|
| Clock No Stretch Mode | Disabled |
| Primary Address Length selection | 7-bit |
| Dual Address Acknowledged | Disabled |
| Primary slave address | 0 |
| General Call address detection | Disabled |

5.2. I2C2

I2C: I2C

5.2.1. Parameter Settings:

Master Features:

| | |
|----------------------|---------------|
| I2C Speed Mode | Standard Mode |
| I2C Clock Speed (Hz) | 100000 |

Slave Features:

| | |
|----------------------------------|----------|
| Clock No Stretch Mode | Disabled |
| Primary Address Length selection | 7-bit |
| Dual Address Acknowledged | Disabled |
| Primary slave address | 0 |
| General Call address detection | Disabled |

5.3. RCC

High Speed Clock (HSE): BYPASS Clock Source
Low Speed Clock (LSE) : Crystal/Ceramic Resonator

5.3.1. Parameter Settings:

System Parameters:

| | |
|-------------------|--------------------|
| VDD voltage (V) | 3.3 |
| Instruction Cache | Enabled |
| Prefetch Buffer | Enabled |
| Data Cache | Enabled |
| Flash Latency(WS) | 2 WS (3 CPU cycle) |

RCC Parameters:

| | |
|--------------------------------|----------|
| HSI Calibration Value | 16 |
| TIM Prescaler Selection | Disabled |
| HSE Startup Timeout Value (ms) | 100 |
| LSE Startup Timeout Value (ms) | 5000 |

Power Parameters:

| | |
|-------------------------------|---------------------------------|
| Power Regulator Voltage Scale | Power Regulator Voltage Scale 1 |
|-------------------------------|---------------------------------|

5.4. SDIO

Mode: SD 4 bits Wide bus

5.4.1. Parameter Settings:

SDIO parameters:

| | |
|-----------------------------|---|
| SDIOCLK clock divide factor | 0 |
|-----------------------------|---|

5.5. SPI1

Mode: Full-Duplex Master

5.5.1. Parameter Settings:

Basic Parameters:

| | |
|--------------|-----------|
| Frame Format | Motorola |
| Data Size | 8 Bits |
| First Bit | MSB First |

Clock Parameters:

| | |
|---------------------------|-----------------------|
| Prescaler (for Baud Rate) | 2 |
| Baud Rate | 42.0 MBits/s * |
| Clock Polarity (CPOL) | Low |
| Clock Phase (CPHA) | 1 Edge |

Advanced Parameters:

| | |
|-----------------|----------|
| CRC Calculation | Disabled |
| NSS Signal Type | Software |

5.6. SYS

Timebase Source: SysTick

5.7. TIM3

Clock Source : Internal Clock

5.7.1. Parameter Settings:

Counter Settings:

| | |
|---|---------------|
| Prescaler (PSC - 16 bits value) | 1000 * |
| Counter Mode | Up |
| Counter Period (AutoReload Register - 16 bits value) | 1000 * |
| Internal Clock Division (CKD) | No Division |

Trigger Output (TRGO) Parameters:

| | |
|-------------------------|--|
| Master/Slave Mode | Disable (no sync between this TIM (Master) and its Slaves) |
| Trigger Event Selection | Reset (UG bit from TIMx_EGR) |

5.8. USART2

Mode: Asynchronous

5.8.1. Parameter Settings:

Basic Parameters:

| | |
|-------------|---------------------------|
| Baud Rate | 115200 |
| Word Length | 8 Bits (including Parity) |
| Parity | None |

| | |
|-----------------------------|----------------------|
| Stop Bits | 1 |
| Advanced Parameters: | |
| Data Direction | Receive and Transmit |
| Over Sampling | 16 Samples |

5.9. FATFS

mode: SD Card

5.9.1. Set Defines:

Version:

| | |
|---------------|-------|
| FATFS version | R0.11 |
|---------------|-------|

Function Parameters:

| | |
|-------------------------------------|------------------------------------|
| FS_TINY (Tiny mode) | Disabled |
| FS_READONLY (Read-only mode) | Disabled |
| FS_MINIMIZE (Minimization level) | Disabled |
| USE_STRFUNC (String functions) | Enabled with LF -> CRLF conversion |
| USE_FIND (Find functions) | Disabled |
| USE_MKFS (Make filesystem function) | Enabled |
| USE_FORWARD (Forward function) | Disabled |
| USE_LABEL (Volume label functions) | Disabled |
| USE_FASTSEEK (Fast seek function) | Enabled |

Locale and Namespace Parameters:

| | |
|----------------------------------|-------------------|
| CODE_PAGE (Code page on target) | Latin 1 (Windows) |
| USE_LFN (Use Long Filename) | Disabled |
| MAX_LFN (Max Long Filename) | 255 |
| LFN_UNICODE (Enable Unicode) | ANSI/OEM |
| STRF_ENCODE (Character encoding) | UTF-8 |
| FS_RPATH (Relative Path) | Disabled |

Physical Drive Parameters:

| | |
|---|----------|
| VOLUMES (Logical drives) | 1 |
| MAX_SS (Maximum Sector Size) | 512 |
| MIN_SS (Minimum Sector Size) | 512 |
| MULTI_PARTITION (Volume partitions feature) | Disabled |
| USE_TRIM (Erase feature) | Disabled |
| FS_NOFSINFO (Force full FAT scan) | 0 |

System Parameters:

| | |
|---------------------------------|-------------------|
| FS_NORTC (Timestamp feature) | Dynamic timestamp |
| NORTC_YEAR (Year for timestamp) | 2015 |

| | |
|---|---------------|
| NORTC_MON (Month for timestamp) | 6 |
| NORTC_MDAY (Day for timestamp) | 4 |
| WORD_ACCESS (Platform dependent access option) | Byte access |
| FS_REENTRANT (Re-Entrancy) | Disabled |
| FS_TIMEOUT (Timeout ticks) | 1000 |
| SYNC_t (O/S sync object) | osSemaphoreId |
| FS_LOCK (Number of files opened simultaneously) | 2 |

5.9.2. IPs instances:

SDIO/SDMMC:

| | |
|---------------|------|
| SDIO instance | SDIO |
|---------------|------|

* User modified value

6. System Configuration

6.1. GPIO configuration

| IP | Pin | Signal | GPIO mode | GPIO pull/up pull down | Max Speed | User Label |
|--------|----------------|---------------|-------------------------------|-----------------------------|-------------|------------|
| I2C1 | PB6 | I2C1_SCL | Alternate Function Open Drain | Pull-up | Very High * | |
| | PB7 | I2C1_SDA | Alternate Function Open Drain | Pull-up | Very High * | |
| I2C2 | PB10 | I2C2_SCL | Alternate Function Open Drain | Pull-up | Very High * | |
| | PB3 | I2C2_SDA | Alternate Function Open Drain | Pull-up | Very High * | |
| RCC | PC14-OSC32_IN | RCC_OSC32_IN | n/a | n/a | n/a | |
| | PC15-OSC32_OUT | RCC_OSC32_OUT | n/a | n/a | n/a | |
| | PH0 - OSC_IN | RCC_OSC_IN | n/a | n/a | n/a | |
| | PH1 - OSC_OUT | RCC_OSC_OUT | n/a | n/a | n/a | |
| SDIO | PA6 | SDIO_CMD | Alternate Function Push Pull | No pull-up and no pull-down | Very High | |
| | PB15 | SDIO_CK | Alternate Function Push Pull | No pull-up and no pull-down | Very High | |
| | PC8 | SDIO_D0 | Alternate Function Push Pull | No pull-up and no pull-down | Very High | |
| | PC9 | SDIO_D1 | Alternate Function Push Pull | No pull-up and no pull-down | Very High | |
| | PA9 | SDIO_D2 | Alternate Function Push Pull | No pull-up and no pull-down | Very High | |
| | PC11 | SDIO_D3 | Alternate Function Push Pull | No pull-up and no pull-down | Very High | |
| SPI1 | PA5 | SPI1_SCK | Alternate Function Push Pull | No pull-up and no pull-down | Very High * | |
| | PA7 | SPI1_MOSI | Alternate Function Push Pull | No pull-up and no pull-down | Very High * | |
| | PB4 | SPI1_MISO | Alternate Function Push Pull | No pull-up and no pull-down | Very High * | |
| USART2 | PA2 | USART2_TX | Alternate Function Push Pull | Pull-up | Very High * | |
| | PA3 | USART2_RX | Alternate Function Push Pull | Pull-up | Very High * | |

6.2. DMA configuration

| DMA request | Stream | Direction | Priority |
|-------------|--------------|----------------------|----------|
| SDIO_RX | DMA2_Stream3 | Peripheral To Memory | Low |

SDIO_RX: DMA2_Stream3 DMA request Settings:

Mode: **Peripheral Flow Control ***

Use fifo: **Enable ***

FIFO Threshold: Full

Peripheral Increment: Disable

Memory Increment: **Enable ***

Peripheral Data Width: **Word ***

Memory Data Width: Word

Peripheral Burst Size: **4 Increment ***

Memory Burst Size: 4 Increment

6.3. NVIC configuration

| Interrupt Table | Enable | Preenmption Priority | SubPriority |
|---|--------|----------------------|-------------|
| Non maskable interrupt | true | 0 | 0 |
| Hard fault interrupt | true | 0 | 0 |
| Memory management fault | true | 0 | 0 |
| Pre-fetch fault, memory access fault | true | 0 | 0 |
| Undefined instruction or illegal state | true | 0 | 0 |
| System service call via SWI instruction | true | 0 | 0 |
| Debug monitor | true | 0 | 0 |
| Pendable request for system service | true | 0 | 0 |
| System tick timer | true | 0 | 0 |
| TIM3 global interrupt | true | 2 | 0 |
| USART2 global interrupt | true | 6 | 0 |
| DMA2 stream3 global interrupt | true | 0 | 0 |
| PVD interrupt through EXTI line 16 | unused | | |
| Flash global interrupt | unused | | |
| RCC global interrupt | unused | | |
| I2C1 event interrupt | unused | | |
| I2C1 error interrupt | unused | | |
| I2C2 event interrupt | unused | | |
| I2C2 error interrupt | unused | | |
| SPI1 global interrupt | unused | | |
| SDIO global interrupt | unused | | |
| FPU global interrupt | unused | | |

* User modified value

7. Power Consumption Calculator report

7.1. Microcontroller Selection

| | |
|-----------|---------------|
| Series | STM32F4 |
| Line | STM32F411 |
| MCU | STM32F411RETx |
| Datasheet | 026289_Rev4 |

7.2. Parameter Selection

| | |
|-------------|-----|
| Temperature | 25 |
| Vdd | 3.6 |

7.3. Battery Selection

| | |
|-------------------|------------------------------|
| Battery | Li-MnO ₂ (CR1225) |
| Capacity | 48.0 mAh |
| Self Discharge | 0.12 %/month |
| Nominal Voltage | 3.0 V |
| Max Cont Current | 1.0 mA |
| Max Pulse Current | 5.0 mA |
| Cells in series | 1 |
| Cells in parallel | 1 |

8. Software Project

8.1. Project Settings

| Name | Value |
|-----------------------------------|--|
| Project Name | sd_LEDSigne_v100 |
| Project Folder | D:\work\LED_Sign\STM32_SD\sd_LEDSigne_v100 |
| Toolchain / IDE | MDK-ARM V5 |
| Firmware Package Name and Version | STM32Cube FW_F4 V1.13.0 |

8.2. Code Generation Settings

| Name | Value |
|---|---|
| STM32Cube Firmware Library Package | Copy all used libraries into the project folder |
| Generate peripheral initialization as a pair of '.c/.h' files | No |
| Backup previously generated files when re-generating | No |
| Delete previously generated files when not re-generated | Yes |
| Set all free pins as analog (to optimize the power consumption) | No |