

Note: Apply and Save commands not shown. Please select these as and when appropriate

VMDC

1. Set a Name for the Macro
2. Click on Display
3. Click on Related Camera unless you want to pick a specific camera below. related means that any camera with an alarm will show on the alarm monitor.
4. Set a duration that the Alarmed camera will be shown by the VMDC monitor

5. Select the monitor to be used for Alarms
6. Check Auto as shown

Alarm Setup

Site Name : VMDC IP Address: 10.0.1.12

Enable External Alarm **7**

Alarm Activity Time

Active From: 12:30:29 To: 12:30:29 [Next Day](#)

Sun Mon Tue Wed Thu Fri Sat

Active From: 12:30:29 To: 12:30:29 [Next Day](#)

Sun Mon Tue Wed Thu Fri Sat

Macro

8 Name:

Description:

Linked to related devices:

7. Check Enable
8. Select Macro created in first step

ViconNet

Macro Editor

Site Name: BUILDING-NVR IP Address: 10.0.1.16

Macro Name	Macro Description	Macro Type
Send to VMDC		Regular

Macro

9 Macro Name: User Name: admin User Priority: 1

Description:

10 **Send Alarm** Destination: VMDC

11 Destination:

9. Set Name for Macro
10. Select Send Alarm
11. Select Destination VMDC

Active Detectors & Associated Macros
Site Name: BUILDING-NVR IP Address: 10.0.1.16

Display Settings
 Always display alarm dialog Display alarm message for 10 Seconds Don't display alarms Play Alarm Siren Save alarm as bookmark

Setup new detector or edit one from

Detector Name

Alarm Setup Wizard
Site Name: BUILDING-NVR IP Address: 10.0.1.16

Select the detector to be activated

12. Add Detector
13. Select External Alarm

13 External alarm
Video analytics alarm

Detector Name:
External alarm

Detector Type:
External alarm

External alarm - An alarm received from another station. It contains the detector name along with the Related Cameras. Continue this setup and associate a Macro to the External Alarm. If this Macro includes actions with Related Cameras then they will be recorded/displayed

12 Add Detector
Edit Detector
Delete Detector
Delete All Detectors
Show Details

<< Back Next >> Finish Cancel

Alarm Setup Wizard
Site Name: BUILDING-NVR IP Address: 10.0.1.16

Device Name: External alarm (External alarm)

Select a macro to run when this detector is activated
You can select one regular macro and one switcher macro.
To create a new macro, go to Macro Editor.

14. Select Macro written in previous step

Macro

Name: **Send to VMDC**
Description:
Linked to related devices: No

Matrix

Name: -----NONE-----
Description:
Linked to related devices:

Macro Editor

<< Back Next >> Finish Cancel

END